

P R B X

POWERBOX Industrial Line
 T20AW Series
 20W 4:1 Single Output
 DC/DC Converter
 Manual



Table of Contents

Output specification	P2
Input specification	P3
General specification	P4
Environmental specifications	P4
EMC characteristics	P4
Characteristic curves	P5
Input source impedance	P21
Output over current protection	P21
Output over voltage protection	P21
Output voltage adjustment	P21
Short circuitry protection	P23
Thermal consideration	P23
Remote on/off control	P23
Heat-sink	P24
Mechanical data	P24
Recommended pad layout	P24
Soldering considerations	P25
Packing information	P25
Safety and installation instruction	P25
MTBF and reliability	P25

Introduction

The T20AW single output series offer 20 watts of output power from a 2.00 X 1.00 X 0.40 inch package. The T20AW single output series with 4:1 ultra wide input voltage of 9~36VDC, 18~75VDC. The T20AW single output series features 1600VDC of isolation, short circuit and over voltage protection, as well as six sided shielding. All models are particularly suited to telecommunications, industrial, mobile telecom and test equipment applications.

DC/DC Converter Features

Single output current to 5.5A
20 watts maximum output power
4:1 ultra wide input voltage range of 9~36 and 18~75VDC
Six-sided continuous shield
Case grounding
High efficiency up to 88%
Low profile 2.00 x 1.00 x 0.40 inch (50.8 x 25.4 x 10.22mm)
Fixed switching frequency
RoHS Directive compliant
No minimum load
Input to output isolation 1600VDC, min
Operating case temperature range 105°C , max
Input under-voltage protection
Output over-voltage protection
Over-current protection, auto-recovery
Output short circuit protection
Remote on/off

Options

Heat-sink available for extended operation
Remote on/off logic configuration

POWERBOX Industrial Line
 T20AW Series
 20W 4:1 Single Output
 DC/DC Converter
 Manual

Output Specifications

Parameters	Model	Min	Typ	Max	Unit
Output voltage range (Vin = Vin(nom) , full load , TA=25°C)	□□S3P3W □□S05W □□S12W □□S15W	3.267 4.95 11.88 14.85	3.300 5.00 12.00 15.00	3.333 5.05 12.12 15.15	VDC
Line regulation (LL to HL at full load)	All	-0.2		+0.2	%
Load regulation (min to 100% full load)	All	-0.5		+0.5	%
<i>Output ripple and noise</i>					
Peak-to-peak (20MHz bandwidth) (Measured with a 0.1µF/50V MLCC)	□□S3P3W Others		60 75		mVp-p mVp-p
Temperature coefficient	All	-0.02		+0.02	%/°C
Output voltage overshoot (Vin(min) to Vin(max) full load; Ta=25°C)	All		0	5	% of Vout
<i>Dynamic load response (Vin = Vin(nom) ; TA=25°C)</i>					
Load step change from 75% to 100% or 100 to 75% of full load					
Peak Deviation	All		250		mV
Setting Time (Vout<10% peak deviation)	All		250		µs
Output current	□□S3P3W □□S05W □□S12W □□S15W	0 0 0 0		5500 4000 1670 1330	mA
Output over voltage protection (zener diode clamp)	□□S3P3W □□S05W □□S12W □□S15W		3.9 6.2 15 18		VDC
Output over current protection	All		150		% of FL
Output short circuit protection	All		Hiccups, automatics recovery		

POWERBOX Industrial Line
 T20AW Series
 20W 4:1 Single Output
 DC/DC Converter
 Manual

Input Specifications

Parameters	Model	Min	Typ	Max	Unit
Operating input voltage	24S□□W 48S□□W	9 18	24 48	36 75	VDC
<i>Input voltage</i>					
Continuous	24S□□W 48S□□W			36 75	VDC
Transient (100mS maximum)	24S□□W 48S□□W			50 100	VDC
Input voltage variation (complies with ETS300 132 part 4.4)	All			5	V/mS
<i>Input current</i>					
(maximum value at Vin=Vin(nom), full load)	24S3P3W 24S05W 24S12W 24S15W 48S3P3W 48S05W 48S12W 48S15W			934 992 1018 1014 467 496 503 501	mA
<i>Input standby current</i>					
(typical value at Vin=Vin(nom), no load)	24S3P3W 24S05W 24S12W 24S15W 48S3P3W 48S05W 48S12W 48S15W			50 65 22 22 35 35 15 15	mA
Under voltage lockout turn-on threshold	24S□□W 48S□□W		9 18		VDC
Under voltage lockout turn-off threshold	24S□□W 48S□□W		7.5 15		VDC
Input reflected ripple current (5 to 20MHz, 12µH source impedance)	All		20		mAp-p
<i>Start up time (Vin = Vin(nom) and constant resistive load)</i>					
Power up	All		20	40	mS
Remote on/off	All		20	40	mS
<i>Remote on/off control (the CTRL pin voltage is referenced to -INPUT)</i>					
CTRL pin high voltage (remote on)	All	3		12	VDC
CTRL pin low voltage (remote off)	All	0		1.2	VDC
Remote off state input current	All		2.5		mA
Input current of remote control pin	All	-0.5		0.5	mA

POWERBOX Industrial Line
 T20AW Series
 20W 4:1 Single Output
 DC/DC Converter
 Manual

General Specifications

Parameters	Model	Min	Typ	Max	Unit
<i>Efficiency</i>					
(Vin = Vin(nom) , Full Load , TA=25°C)	24S3P3W	85			%
	24S05W	88			%
	24S12W	86			%
	24S15W	86			%
	48S3P3W	85			%
	48S05W	88			%
	48S12W	87			%
	48S15W	87			%
<i>Isolation voltage (1 minute)</i>					
Input to output	All	1600			VDC
Input to case, output to case	All	1600			VDC
Isolation resistance	All	1			GΩ
Isolation capacitance	All			1500	pF
Switching frequency	All	360	400	440	kHz
Weight	All		27		g
MTBF MIL-HDBK-217F	All			1.851 x 10 ⁶	hours
Case material	All	Nickel-coated copper			
Base material	All	FR4 PCB			
Potting material	All	Epoxy (UL94 V-0)			
Dimensions	All	50.8 x 25.4 x 10.2 mm (2.00 x 1.00 x 0.40 inch)			

Environmental Specifications

Parameters	Model	Min	Typ	Max	Unit
Operating ambient temperature (without derating)*	All	-40		66	°C
Operating ambient temperature (with derating)*	All	66		105	°C
Operating case temperature	All			105	°C
Storage temperature	All	-55		125	°C
<i>Thermal impedance</i>					
Natural convection	All		12		°C/W
Natural convection with heat-sink	All		10		°C/W
Thermal shock	All	MIL-STD-810F			
Vibration	All	MIL-STD-810F			
Relative humidity	All	5		95	% RH

*Test condition with vertical direction by natural convection (20LFM)

EMC Characteristics

Parameters	Standard	Condition	Level
EMI*	EN55022		Class A
ESD	EN61000-4-2	Air Contact	±8kV ±6kV
Radiated Immunity	EN61000-4-3		10V/m
Fast transient**	EN61000-4-4		±2kV
Surge**	EN61000-4-5		±1kV
Conducted immunity	EN61000-4-6		10V r.m.s
Power frequency magnetic field	EN61000-4-8	100A/m continuous; 1000A/m 1 second	Perf. Criteria A

*An external input filter capacitor is required if the module has to meet EN61000-4-4, EN61000-4-5.

The filter capacitor Powerbox suggest: Nippon chemi-con KY series, 220μF/100V, ESR 48mΩ.

POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S3P3W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S3P3W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S05W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S05W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S12W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S12W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S15W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-24S15W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-48S3P3W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output


DC/DC Converter

Manual


All test conditions are at 25°C. The figures are identical for PMD20-48S3P3W




Typical Output Ripple and Noise.
 $V_{in} = V_{in(\text{nom})}$, Full Load




Transient Response to Dynamic Load Change from
100% to 75% to 100% of Full Load, $V_{in} = V_{in(\text{nom})}$




Typical Input Start-Up and Output Rise Characteristic
 $V_{in} = V_{in(\text{nom})}$, Full Load



Using ON/OFF Voltage Start-Up and V_o Rise Characteristic
 $V_{in} = V_{in(\text{nom})}$, Full Load



Conduction Emission of EN55022 Class A
 $V_{in} = V_{in(\text{nom})}$, Full Load



Conduction Emission of EN55022 Class B
 $V_{in} = V_{in(\text{nom})}$, Full Load

POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-48S05W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-48S05W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-48S12W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-48S12W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual

All test conditions are at 25°C. The figures are identical for PMD20-48S15W



POWERBOX Industrial Line


T20AW Series

20W 4:1 Single Output


DC/DC Converter

Manual


All test conditions are at 25°C. The figures are identical for PMD20-48S15W




Typical Output Ripple and Noise.
Vin=Vin(nom) , Full Load




Transient Response to Dynamic Load Change from
100% to 75% to 100% of Full Load, Vin=Vin(nom)




Typical Input Start-Up and Output Rise Characteristic
Vin=Vin(nom) , Full Load



Using ON/OFF Voltage Start-Up and Vo Rise Characteristic
Vin=Vin(nom) , Full Load



Conduction Emission of EN55022 Class A
Vin=Vin(nom) , Full Load



Conduction Emission of EN55022 Class B
Vin=Vin(nom) , Full Load

POWERBOX Industrial Line
T20AW Series
20W 4:1 Single Output
DC/DC Converter
Manual

Input Source Impedance

The power module should be connected to a low impedance input source. Highly inductive source impedance can affect the stability of the power module. Input external L-C filter is recommended to minimize input reflected ripple current. The inductor is simulated source impedance of $12\mu\text{H}$ and capacitor is Nippon chemi-con KZE series $220\mu\text{F}/100\text{V}$. The capacitor must as close as possible to the input terminals of the power module for lower impedance.

Output Over Current Protection

When excessive output currents occur in the system, circuit protection is required on all power supplies. Normally, overload current is maintained at approximately 150 percent of rated current for T20AW-S SERIES. Hiccup-mode is a method of operation in a power supply whose purpose is to protect the power supply from being damaged during an over-current fault condition. It also enables the power supply to restart when the fault is removed. There are other ways of protecting the power supply when it is over-loaded, such as the maximum current limiting or current foldback methods.

One of the problems resulting from over current is that excessive heat may be generated in power devices, especially MOSFET and Schottky diodes and the temperature of those devices may exceed their specified limits. A protection mechanism has to be used to prevent those power devices from being damaged.

The operation of hiccup is as follows. When the current sense circuit sees an over-current event, the controller shuts off the power supply for a given time and then tries to start up the power supply again. If the over-load condition has been removed, the power supply will start up and operate normally, otherwise, the controller will see another over-current event and shut off the power supply again, repeating the previous cycle. Hiccup operation has none of the drawbacks of the other two protection methods, although its circuit is more complicated because it requires a timing circuit. The excess heat due to overload lasts for only a short duration in the hiccup cycle, hence the junction temperature of the power devices is much lower.

The hiccup operation can be done in various ways. For example, one can start hiccup operation any time an over-current event is detected, or prohibit hiccup during a designated start-up is usually larger than during normal operation and it is easier for an over-current event is detected, or prohibit hiccup during a designated start-up interval (usually a few milliseconds). The reason for the latter operation is that during start-up, the power supply needs to provide extra current to charge up the output capacitor. Thus the current demand during start-up is usually larger than during normal operation and it is easier for an over-current event to


occur. If the power supply starts to hiccup once there is an over-current, it might never start up successfully. Hiccup mode protection will give the best protection for a power supply against over current situations, since it will limit the average current to the load at a low level, so reducing power dissipation and case temperature in the power devices.

Output Over Voltage Protection

The output over-voltage protection consists of output Zener diode that monitors the voltage on the output terminals. If the voltage on the output terminals exceeds the over-voltage protection threshold, then the Zener diode clamps the output voltage.

Output Voltage Adjustment

Output voltage set point adjustment allows the user to increase or decrease the output voltage set point of a module. This is accomplished by connecting an external resistor between the TRIM pin and either the +OUTPUT or -OUTPUT pins. With an external resistor between the TRIM and -OUTPUT pin, the output voltage set point increases. With an external resistor between the TRIM and +OUTPUT pin, the output voltage set point decreases. The external TRIM resistor needs to be at least 1/16W resistors.



POWERBOX Industrial Line

T20AW Series

20W 4:1 Single Output

DC/DC Converter

Manual


Trim Table

PMD20-□□S3P3W		Trim-Up									
Trim-Up	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		3.333	3.366	3.399	3.432	3.465	3.498	3.531	3.564	3.597	3.630
RU (K Ohms)=		57.930	26.165	15.577	10.283	7.106	4.988	3.476	2.341	1.459	0.753
PMD20-□□S3P3W		Trim-Down									
Trim-Down	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		3.267	3.234	3.201	3.168	3.135	3.102	3.069	3.036	3.003	2.970
RD (K Ohms)=		69.470	31.235	18.490	12.117	8.294	5.745	3.924	2.559	1.497	0.647
PMD20-□□S05W		Trim-Up									
Trim-Up	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		5.050	5.100	5.150	5.200	5.250	5.300	5.350	5.400	5.450	5.500
RU (K Ohms)=		36.570	16.580	9.917	6.585	4.586	3.253	2.302	1.588	1.032	0.588
PMD20-□□S05W		Trim-Down									
Trim-Down	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		4.950	4.900	4.850	4.800	4.750	4.700	4.650	4.600	4.550	4.500
RD (K Ohms)=		45.533	20.612	12.306	8.152	5.660	3.999	2.812	1.922	1.230	0.676
PMD20-□□S12W		Trim-Up									
Trim-Up	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		12.120	12.240	12.360	12.480	12.600	12.720	12.840	12.960	13.080	13.200
RU (K Ohms)=		367.908	165.954	98.636	64.977	44.782	31.318	21.701	14.488	8.879	4.391
PMD20-□□S12W		Trim-Down									
Trim-Down	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		11.880	11.760	11.640	11.520	11.400	11.280	11.160	11.040	10.920	10.800
RD (K Ohms)=		460.992	207.946	123.597	81.423	56.118	39.249	27.199	18.162	11.132	5.509
PMD20-□□S15W		Trim-Up									
Trim-Up	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		15.150	15.300	15.450	15.600	15.750	15.900	16.050	16.200	16.350	16.500
RU (K Ohms)=		404.184	180.592	106.061	68.796	46.437	31.531	20.883	12.898	6.687	1.718
PMD20-□□S15W		Trim-Down									
Trim-Down	(%)	1	2	3	4	5	6	7	8	9	10
VOUT (Volts)=		14.850	14.700	14.550	14.400	14.250	14.100	13.950	13.800	13.650	13.500
RD (K Ohms)=		499.816	223.408	131.272	85.204	57.563	39.136	25.974	16.102	8.424	2.282

POWERBOX Industrial Line
 T20AW Series
 20W 4:1 Single Output
 DC/DC Converter
 Manual


Heat-Sink Considerations

Equip Heat-sink (7G-0020C-F) for lower temperature and higher reliability of the module. Considering space and air-flow is the way to choose which Heat-sink is needed.



All dimensions in inch (mm)

Mechanical Data




1. All dimensions in inch (mm)
2. Tolerance: $X.XX \pm 0.02$ ($X.X \pm 0.5$)
 $X.XXX \pm 0.01$ ($X.XX \pm 0.25$)
3. Pin pitch tolerance ± 0.01 (0.25)
4. Pin dimension tolerance ± 0.014 (0.35)

Pin Connection


Pin	Define
1	+ INPUT
2	- INPUT
3	+ OUTPUT
4	TRIM
5	- OUTPUT
6	CTRL

External Output Trimming

Output can be externally trimmed by using the method shown below.



Recommended Pad Layout




1. All dimensions in inch (mm)
2. Tolerance: $X.XX \pm 0.02$ ($X.X \pm 0.5$)
 $X.XXX \pm 0.01$ ($X.XX \pm 0.25$)
3. Pin pitch tolerance ± 0.01 (0.25)

POWERBOX Industrial Line
 T20AW Series
 20W 4:1 Single Output
 DC/DC Converter
 Manual

Soldering Considerations


Lead free wave solder profile for DIP type.



Zone	Reference Parameter
Preheat zone	Rise temp. speed : 3°C/ sec max. Preheat temp.: 100~130°C
Actual heating	Peak temp. : 250~260°C Peak time (T1+T2 time) : 4~6 sec

Reference Solder: Sn-Ag-Cu , Sn-Cu
 Hand Welding: Soldering iron: Power 90W
 Welding Time: 2~4 sec
 Temp.: 380~400°C

Packing Information



10 pcs per tube.

Safety and Installation Instruction

Fusing Consideration

Caution: This power module is not internally fused. An input line fuse must always be used. This encapsulated power module can be used in a wide variety of applications, ranging from simple stand-alone operation to an integrated part of sophisticated power architecture. To maximum flexibility, internal fusing is not included, however, to achieve maximum safety and system protection, always use an input line fuse. The safety agencies require a slow-blow fuse with maximum rating of 6A. Based on the information provided in this data sheet on Inrush energy and maximum dc input current, the same type of fuse with lower rating can be used. Refer to the fuse manufacturer's data for further information.

MTBF and Reliability

The MTBF of T20AW SINGLE-SERIES of DC/DC converters has been calculated using MIL-HDBK 217F @Ta=25°C, FULL LOAD. The resulting figure for MTBF is 1.851×10^6 hours.